

**Page:** 1 of 4


Work procedure: Replaceing KL kiosk transformer.

.Unplug the light supply from the GPO





2. Remove the earth bar from the Transformer 3.Remove 6 X Enclosure fixing bolts. 3 on each end of the Kiosk.



This document is uncontrolled and intended to be used as a guide to replacing equipment in the field. Schneider Electric have not commented or issued any reference to OH&S or Quality procedures which are the responsibility of Ausgrid.

4. Remove 6 X Enclosure fixing bolts. 3 on each end of the Kiosk.



5. Remove plug bolts from the enclosure's four lifting points.



6. Fit appropriate lifting rings and tighten







Requirement Point

7. Place protective sheet under each lifting ring.



8. Attach crane to enclosure.



9. Remove enclosure gently. Spotter to ensure the enclosure does not get caught on the TX or fittings.

