

Work procedure: Replaceing KL kiosk transformer. This document is uncontrolled and 17. Replace supplied washer set with 18. LV flexible fastener kit shown with 19. Prepare 1st fishplate with bolt and intended to be used as a guide to 8mm Belleville washers belleville washers replacing supplied belleville washer. replacing equipment in the field. stock. Schneider Electric have not commented or issued any reference to OH&S or Quality procedures which are the responsibility of Ausgrid. 22. Repeat steps 38 to 40 to complete 20. Fit fishplates to both sides of flexible 21. Apply Belleville washer and nut. each flexible ioint. (Hand tighten.) ioint. Leave this bolt un-fastened on each terminal. 23. Flexibles fitted showing 4th bolt on 24. Tighten bolts with air ratchet. 25. Locate and set torque wrench to each phase terminal un-fastened. 30Nm.

Page: 3 of 4